



## Smart, Quiet and Energy Efficient

### Connectivity

- **MyQ® Technology** enables you to securely monitor and control your garage door opener and houselights with your smartphone, tablet or computer. (Requires purchase of Internet Gateway (828LM)).
- **Alerts** can be received as email or pop-up (push) notifications on your mobile device so that you always know the status of your garage door and houselights.
- **MyQ mobile app** is a free download requiring no annual activation fee.

### Performance

- **P3™ Motors** are reliable, durable and powerful – designed specifically for your needs.
- **1/2 HP AC motor** with industrial strength belt drive system provides quiet, reliable and maintenance free performance.
- **Motor Vibration Isolation System (MVIS®)** provides super quiet, smooth operation year after year.
- **Energy-efficient** operation consumes up to 75% less power in standby mode.
- **Lifetime motor** and belt warranty. 1-year parts warranty.

### Safety and Security

- **Security+ 2.0®** safeguards your household – with every click a new code is sent to the garage door opener so that the door opens only for you.
- **PosiLock®** locks down your door by electronically monitoring against a forced opening.
- **Alert-2-Close** warning system provides audible and visual warnings when the garage door is about to close when using MyQ Technology.
- **The Protector System®** has safety sensors that project a light beam across the garage door opening, automatically reversing the door if anything interrupts the beam.

### Included Accessories:



**3-Button Remote Control** (893LM)

Allows you to control up to three garage door openers, gate operators or MyQ Light Accessories.



**Multi-Function Control Panel®** (882LM)

Enables you to turn garage door opener lights on and off from inside the garage.

### Optional Accessories:



**Internet Gateway** (828LM)

Connect your MyQ-Enabled Garage Door Opener and Accessories to the Internet with this device.



**Ceiling Mount** (195LM)

Give your garage the style it's been missing by hiding the wires and cords with this sleek ceiling mount. Works in most standard garages.



**Remote Light Control** (825LM)

Allows you to control any lamp with your garage door opener remote control or smartphone via the Internet Gateway and the free MyQ app.



**Door and Gate Monitor** (829LM)

Enables you to monitor and close up to four garage doors or gates from any room in your house.

### SPEC SHEET STANDARD SPECIFICATIONS

#### DIMENSIONS

Installed Length: 128"  
Maximum Door Opening: 7' 6" \*  
Headroom Clearance Required: 2"  
\*Up to 10' with optional 8' or 10' rails

#### CARTONS

Number of Cartons: 2  
Carton 1: Dimensions and Contents:  
- 20" x 12" x 10"  
- 882LM Multi-Function Control Panel  
- 893LM 3-Button Remote Control  
- Garage Door Opener Head  
- The Protector System® Safety Reversing Sensors  
Carton 2: Dimensions and Contents:  
- 10' 4" x 5" x 5"  
- Assembled Solid-Steel T-Rail (Belt)

#### SECURITY+ 2.0® RADIO CONTROLS

Coding System: Smart Receiver Code Button and Indicator Light  
893LM 3-Button Remote Control  
Operating Range: 200' (approximately)  
Operating Temperature: -40°F to 150°F  
Frequency:  
- Remote Control: 310, 315 & 390 MHz Tri-Band  
- Receiver: Frequency Agile on 310, 315 & 390 MHz  
Security+ 2.0 Anti-Burglary Coding

#### MyQ® RADIO

902-928 MHz  
50 Channel FHSS (Frequency Hopping Spread Spectrum)  
Provides two-way communication from garage door opener and MyQ Accessories.  
Enables remote closing of garage door with key MyQ Accessories.  
Enables monitoring and control of garage door openers and lighting controls via computer, tablet or smartphone.\*  
\*Requires Internet Gateway Accessory Model 828LM

#### SECURITY+ 2.0 ENCRYPTED CONTROLS

882LM Multi-Function Control Panel  
- Program Remote Controls  
- Maintenance Alert System

#### CONVENIENCE / SAFETY

The Protector System Safety Reversing Sensors  
Alert-2-Close Unattended Close Operation w/ Select Accessories\*  
Emergency/Quick Release  
Automatic Trolley Reconnect  
Ventilation /Pet Opening  
Down Safety Reverse  
Up Safety Stop  
Door Open/Beam Obstructed/Lights On  
Maintenance Alert System  
PosiLock® secure lock system  
\*Timer-to-close feature requires purchase of 880LM or 881LM control panel and is for sectional doors only, not one piece doors.  
\*Unattended Operation functionality cannot be utilized when opener is installed on a one-piece door.

**For more information  
visit [www.devancocanada.com](http://www.devancocanada.com)**

Note: To reduce the risk of injury to persons, when the Internet Gateway is used with garage door openers, the operator must be installed with sectional doors.

### ELECTRICAL SPECIFICATIONS

#### POWER

Voltage: 120V AC, 60Hz  
Current Rating: 4.5A  
UL Listings: Yes  
Length of Line Cord: 4' (3-prong)

#### ENERGY EFFICIENCY

Approximately 1 Watt Power in Standby Mode\*  
Enhanced CFL (Compact Fluorescent) Compatible  
\*Standby Mode at down limit, work lights off

#### LOGIC TYPE

Solid State Microcontroller with Built-in Surge Suppressor

#### LIGHTING

Number of Bulbs: 2  
Maximum Wattage: 100 x 2  
Adjustable Time, Solid-State Delay  
Enhanced CFL (Compact Fluorescent) Compatible, Max 26 Watts

### MECHANICAL SPECIFICATIONS

#### MOTOR

Horsepower: 1/2  
RPM: 1,625  
Thermal Protection: Automatic  
Lubrication: Permanent

#### DRIVE MECHANISM

Drive Means: Full Reinforced Drive Belt  
Reduction Means: Gear 16:1  
Door Linkage: Adjustable Door Arm

#### ADJUSTMENTS

Auto Force  
Electronic Limit Settings

#### TRAVEL RATE

Approximately 7" per second

#### SHIPPING WEIGHTS

Head: 24 lbs  
Rail: 17 lbs.

#### MATERIALS

Chassis and Chassis Cover: Steel  
Rail: Solid-Steel T  
Trolley: Steel

#### WARRANTY

Lifetime Motor Warranty  
Lifetime Belt Warranty  
1 Year Parts and Accessories Warranty

#### HOMELINK® Compatible (version 4.0 or higher)\*

\*May require an external adapter depending on the model and year of your vehicle.  
Visit [homelink.com](http://homelink.com) for additional information.