



# CAPAC

## DATA SHEET

Smart Access Hub  
SECTION 28 13 00

### Range

CAPAC Feature	Wired	Wireless	Wire Type	Range
Power 6 to 24VDC transformer (from outlet to controller)	x		2 wire (14 AWG) 2 wire (16 AWG) 2 wire (18 AWG)	Up to 300 ft. Up to 200 ft. Up to 100 ft.
Wiegand accessory wiring	x		7 wire (18-22 AWG)	Up to 500 ft.
Relay output wiring	x		2 wire (18-24 AWG)	Up to 2500 ft.
Supervised Input	x		2 wire (18-24 AWG)	Up to 500 ft.
RJ-45 Internet	x		CAT5e or better 8 strand (24 AWG)	Up to 328 ft.
Wi-Fi		x	N/A	Up to 250 ft.**

### Dimensions

